



City of Murray

Lockout Tagout Procedures

Machine: Oxidation Wheel- Ditch 3 Rotor 1 Plant: Wastewater Treatment Plant
 Area: South East Updated: 7/9/10

Personal Protective Equipment:

				
Safety Glasses	Steel Toe Shoes	Leather Gloves (as needed)	Nitrile Gloves (as needed)	

SAFE OPERATING PROCEDURES:

<ol style="list-style-type: none"> 1. Always Lock, Tag, and Try to control hazardous energy sources prior to performing maintenance or service on this machine, when removing or bypassing a guard, and/or under any circumstance where the unexpected start-up or energization of the equipment could cause bodily harm. 	<ol style="list-style-type: none"> 2. Use caution when motor is off due to the flow of the water still turning rotor. 3. There is possible bloodborne pathogen contact associated with working around oxidation wheels.
--	---

LOCKOUT PROCEDURE:

(Use this procedure before any servicing or maintenance activities are performed where the expected energization, start up, or release of stored energy may cause injury. (i.e. repairs, set-up, clearing parts, etc.)

Lock Out/Tag Out Equipment Needed:

					
Lock	Tag	Hasp			

Before Servicing or Maintenance:

<ol style="list-style-type: none"> 1. Notify all affected personnel that you intend to lockout the equipment. 2. Clear the area and equipment of tools, parts and other materials. 3. Identify Ditch 3 Rotor 1 knife switch on the southeast first floor of the Filter Press Building located on the right side of the control panel. 4. Denergize knife switch by pulling to OFF position. 	<ol style="list-style-type: none"> 5. Apply hasp, lock, and tag on knife switch. *NOTE* Tag shall include date taken out of service, person/persons that took out of service, and work being done. 6. Dissipate or release any stored energy by trying to turn knife switch ON at box located next to the motor. 7. Return knife switch to OFF position.
---	---

Energy Sources:				
Magnitude:	460V			
Energy Isolation Device & Location:	Control Panel in Filter Press Building			

After Servicing or Maintenance:

<ol style="list-style-type: none"> 1. Verify all controls are "off" or in neutral position. 2. Clear machine or equipment of tools, parts, or people. 3. Make sure all guarding is in place. 4. Notify affected personnel that the machine or equipment will be re-energized. 5. Remove locks, devices, and tags from energy isolation devices. 6. Re-energize or power-up machine by returning energy isolating devices to normal operating position. 	Prepared by: _____ Date: <u>7/9/10</u> Approvals: _____ _____ _____ _____
--	---